

A25: Creating Frequency Groups

1. Press CLR/DEL to select frequency entry mode, if not already there.
2. Enter your frequency with the keypad or tuning dial.
3. Press the F key and then press MR/MW.
4. Using the tuning knob, scroll down the list on the Display and highlight **Group**.
5. Press ENT/ANL.
6. Using the tuning knob, highlight the Group number you wish to use.
7. Press ENT/ANL.
8. Using the tuning knob, go up in the list and highlight **Write**.
9. Press ENT/ANL.
10. At the Prompt **Write ?**, highlight **Yes** and press ENT/ANL.
11. The word **Completed** will appear.
12. To select a Group, press MR/MW to enter memory mode.
13. Next, press the F key then press the GROUP key.
14. Using the tuning knob, highlight the Group number you wish to use.
15. Press ENT/ANL.

Selecting a Group

1. Enter memory mode by pressing MR/MW.
2. Press the F key then press the GROUP key.
3. Using the tuning knob, highlight the Group that you wish to use.
4. Press ENT/ANL.

All of the frequencies that you have entered into this Group will be selectable with the tuning knob.